LCD-Monitor

Chassis : LS22TDS / LS20TDS

Model : T220M / T200M

SERVICE Manual

TFT-LCD Monitor

T220M / T200M

Contens

Refer to the service manual in the GSPN (see the rear cover) for the more information.

Contents

GSPN (Global Service Partner Network)

Area	Web Site
North America	http://service.samsungportal.com
Latin America	http://latin.samsungportal.com
CIS	http://cis.samsungportal.com
Europe	http://europe.samsungportal.com
China	http://china.samsungportal.com
Asia	http://asia.samsungportal.com
Mideast & Africa	http://mea.samsungportal.com

Printed in Korea
P/N: BN82-00479A-00

1. Precautions

1-1. Safety Precautions

Follow these safety, servicing and ESD precautions to prevent damage and to protect against potential hazards such as electrical shock.

1-1-1. Warnings

1. For continued safety, do not attempt to modify the circuit board.
2. Disconnect the AC power and DC power jack before servicing.

1-1-2. Servicing the LCD Monitor

1. When servicing the LCD Monitor, Disconnect the AC line cord from the AC outlet.
2. It is essential that service technicians have an accurate voltage meter available at all times. Check the calibration of this meter periodically.

1-1-3. Fire and Shock Hazard

Before returning the monitor to the user, perform the following safety checks:

1. Inspect each lead dress to make certain that the leads are not pinched or that hardware is not lodged between the chassis and other metal parts in the monitor.
2. Inspect all protective devices such as nonmetallic control knobs, insulating materials, cabinet backs, adjustment and compartment covers or shields, isolation resistorcapacitor networks, mechanical insulators, etc.
3. Leakage Current Hot Check (Figure 1-1):
   WARNING : Do not use an isolation transformer during this test.
   Use a leakage current tester or a metering system that complies with American National Standards Institute (ANSI C101.1, Leakage Current for Appliances), and Underwriters Laboratories (UL Publication UL1410, 59.7).



Figure 1-1. Leakage Current Test Circuit

4. With the unit completely reassembled, plug the AC line cord directly into a 120V AC outlet. With the unit's AC switch first in the ON position and then OFF, measure the current between a known earth ground (metal water pipe, conduit, etc.) and all exposed metal parts, including: metal cabinets, screwheads and control shafts.
   The current measured should not exceed 0.5 milliamp.
   Reverse the power-plug prongs in the AC outlet and repeat the test.

1-1-4. Product Safety Notices

Some electrical and mechanical parts have special safetyrelated characteristics which are often not evident from visual inspection. The protection they give may not be obtained by replacing them with components rated for higher voltage, wattage, etc. Parts that have special safety characteristics are identified by ⚠ on schematics and parts lists. A substitute replacement that does not have the same safety characteristics as the recommended replacement part might create shock, fire and/or other hazards. Product safety is under review continuously and new instructions are issued whenever appropriate.

1-2. Servicing Precautions

WARNING: An electrolytic capacitor installed with the wrong polarity might explode.
Caution: Before servicing units covered by this service manual, read and follow the Safety Precautions section of this manual.
Note: If unforeseen circumstances create conflict between the following servicing precautions and any of the safety precautions, always follow the safety precautions.

1-2-1 General Servicing Precautions

1. Always unplug the unit's AC power cord from the AC power source and disconnect the DC Power Jack before attempting to:
   (a) remove or reinstall any component or assembly, (b) disconnect PCB plugs or connectors, (c) connect a test component in parallel with an electrolytic capacitor.
2. Some components are raised above the printed circuit board for safety. An insulation tube or tape is sometimes used. The internal wiring is sometimes clamped to prevent contact with thermally hot components. Reinstall all such elements to their original position.
3. After servicing, always check that the screws, components and wiring have been correctly reinstalled. Make sure that the area around the serviced part has not been damaged.
4. Check the insulation between the blades of the AC plug and accessible conductive parts (examples: metal panels, input terminals and earphone jacks).
5. Insulation Checking Procedure: Disconnect the power cord from the AC source and turn the power switch ON. Connect an insulation resistance meter (500 V) to theblades of the AC plug.
   The insulation resistance between each blade of the AC plug and accessible conductive parts (see above) should be greater than 1 megohm.
6. Always connect a test instrument's ground lead to the instrument chassis ground before connecting the positive lead; always remove the instrument's ground lead last.

1-3. Static Electricity Precautions

Some semiconductor (solid state) devices can be easily damaged by static electricity. Such components are commonly called Electrostatically Sensitive Devices (ESD). Examples of typical ESD are integrated circuits and some field-effect transistors. The following techniques will reduce the incidence of component damage caused by static electricity.

1. Immediately before handling any semiconductor components or assemblies, drain the electrostatic charge from your body by touching a known earth ground. Alternatively, wear a discharging wrist-strap device. To avoid a shock hazard, be sure to remove the wrist strap before applying power to the monitor.
2. After removing an ESD-equipped assembly, place it on a conductive surface such as aluminum foil to prevent accumulation of an electrostatic charge.
3. Do not use freon-propelled chemicals. These can generate electrical charges sufficient to damage ESDs.
4. Use only a grounded-tip soldering iron to solder or desolder ESDs.
5. Use only an anti-static solder removal device. Some solder removal devices not classified as "anti-static" can generate electrical charges sufficient to damage ESDs.
6. Do not remove a replacement ESD from its protective package until you are ready to install it. Most replacement ESDs are packaged with leads that are electrically shorted together by conductive foam, aluminum foil or other conductive materials.
7. Immediately before removing the protective material from the leads of a replacement ESD, touch the protective material to the chassis or circuit assembly into which the device will be installed.
   Caution: Be sure no power is applied to the chassis or circuit and observe all other safety precautions.
8. Minimize body motions when handling unpackaged replacement ESDs. Motions such as brushing clothes together, or lifting your foot from a carpeted floor can generate enough static electricity to damage an ESD.

1-4. Installation Precautions

1. For safety reasons, more than two people are required for carrying the product.
2. Keep the power cord away from any heat emitting devices, as a melted covering may cause fire or electric shock.
3. Do not place the product in areas with poor ventilation such as a bookshelf or closet. The increased internal temperature may cause fire.
4. Bend the external antenna cable when connecting it to the product. This is a measure to protect it from being exposed to moisture. Otherwise, it may cause a fire or electric shock.
5. Make sure to turn the power off and unplug the power cord from the outlet before repositioning the product. Also check the antenna cable or the external connectors if they are fully unplugged. Damage to the cord may cause fire or electric shock.
6. Keep the antenna far away from any high-voltage cables and install it firmly. Contact with the highvoltage cable or the antenna falling over may cause fire or electric shock.
7. When installing the product, leave enough space (10cm) between the product and the wall for ventilation purposes. A rise in temperature within the product may cause fire.

Memo

2. Product specifications

2-1. Feature & Specifications

Model	T220M / T200M

Feature

- ▶ Supreme Digital Interface & Networking
  - With a built-in with no particular set-top box and provides simple access with a single remote control.
- ▶ Excellent Picture Quality
  - DNIe technology provides life-like clear images.
- ▶ Dynamic Contrast
  - Automatically detects the input visual signal and adjusts to create optimum contrast.
- ▶ Convenience
  -The TV utilizes the HDMI system to implement perfect digital sound and picture quality.

Specifications			
Item	Description		
	T220M		T200M
LCD Panel	TFT-LCD Panel, RGB Vertical strip, normaly White, 22-Inch viewable, 0.282(H) X 0.282(V)mm Pixel Pitch		TFT-LCD Panel, RGB Vertical strip, normaly White, 20.1-Inch viewable, 0.258(H) X 0.258(V)mm Pixel Pitch
Scanning Frequency	Horizontal : 30KHz ~ 81KHz(Automatic) Vertical: 56Hz ~ 75Hz(Automatic)		Horizontal :30KHz ~ 81KHz(Automatic) Vertical:56Hz ~ 75Hz(Automatic)
Display Colors	16.7 Million colors		16.7Million colors
Maximum resolution	Horizontal: 1680pixels Vertical: 1050pixels		Horizontal : 1680pixels Vertical:1050pixels
Input Signal	Analog 0.7Vp-p±10% positive at 75Ω,internally terminated		Analog 0.7Vp-p±10% positive at 75Ω,internally terminated
Input Sync Signal	Type: separate H/V,composite Level : TTL Level		Type: separate H/V,composite Level : TTL Level
Maximum Pixel Clock rate	146.250MHz		146.250MHz
Active Display (Horizontal/Vertical)	473.76(H) X 296.1(V)		433.44(H) X 270.9(V)
AC power voltage & Frequency	AC 110 ~ 240V, 50 ~ 60 Hz		AC110 ~ 240V, 50 ~ 60Hz
Power Consumption	54W ＜ 2W		50W ＜ 2W
Dimensions Set (W x D x H)	520x215x441.5mm (After installation stand) 520x86.5x373.5mm (Without stand)		486x215x417.5mm (After installation stand) 486x86x350mm (Without stand)
Weight Set (After installation Stand)	6.2kg		6.0kg
TV System	Tuning	Frequency Synthesize	
	System	NT3.58, PAL-M, PAL-N	
	Sound	MONO, STEREO	
Environmental Considerations	Operating Temperature: 50˚C ~ 104˚F(10˚C ~ 40˚C) Operating Humidity : 10% ~ 80% Storage Temperature: -4˚C ~ 113˚C(-20˚C ~ 45˚C) Storage Humidity: 5% ~ 95%		

Specifications		
Item	**Description**	
	T220M	**T200M**
Antenna Input	75Ω	
Sound Characteristic	-MAX Internal speaker Out : Right : 3W / Left : 3W -BASS Control Range : -8 dB ~ + 8dB -TREBLE Control Range : -8 dB ~ +8 dB -Headphone Out : 10 mW MAX -Output Frequency : RF : 80 Hz ~ 15 kHz A/V : 80 Hz ~ 20 kHz	

2-2. Spec Comparison to the Old Models

Model	T220M / T200M	Curie (225MD)
Design		
Screen Size	**20" / 22"**	22"
Frequency **Horizontal** **Vertical** **Display Color**	30 ~ 81 kHz 56 ~ 75 Hz 16,777,216 colors	30 ~ 81 kHz 56 ~ 75 Hz 16,777,216 colors
PC Resolution **Maximum mode**	**WSXGA+, 1680 x 1050 @ 60 Hz**	1680 x 1050
Input Signal **Sync Signal** **Video Signal**	H/V Separate, TTL, P. or N. 0.7 Vp-p @ 75ohm	H/V Separate, TTL, P. or N. 0.7 Vp-p @ 75ohm
Power Consumption **Normal** **Power Saving**	**22" 54W < 2W** **20" 50W < 2W**	58W < 2W

*Color Effect

- Grey scale: Images are displayed in a grey tone on the screen.
- Green: Images are displayed in a green tone on the screen.
- Aqua: Images are displayed in a blue tone on the screen.
- Sepia: Images are displayed in a brown tone on the screen.

Image Size : : If the resolution is not wide resolution, this option allows the screen size to be selected as normal or wide.

2-3. Accessories

Product	Description	Ccde. No	Remark
	Remote Control & Batteries (AAA x 2)	BN59-00678A	Samsung Electronics Service center
	Power Cord	3903-000190	
	Stand Body	BN96-07347D	
	Stand Base	BN96-07345A	
	D-Sub Cable	BN39-00244G	
	User's Guide, Monitor Driver, Natural Color Pro Software	BN96-07540A	
	Cleaning Cloth	BN63-01798A	

3. Disassembly and Assembly

This section describes the disassembly and reassembly sequences for this monitor.

⚠ Warning: As this monitor has parts that are sensitive to static electricity, be careful when handling them.

3-1. Disassembly

⚠ Caution: 1. Turn the monitor off before beginning the disassembly process.
2. When disassembling the monitor, do not use any metal tools except for the provided jig.
3. Remove the signal cable and the power cord before beginning the disassembly.

Description	Photo	Screws
1. Place monitor face down on cushioned table. Remove Stand, then remove 2 marked screws from the rear cover. ⚠ Caution : If you do not tilt the stand and use too much force to remove it, the connection pin may break.		
2. Remove the cover and the LCD panel using the provided jig on both grooves at the bottom. ⚠ Caution : Remove the cover and the LCD panel using the provided jig on both grooves at the bottom.		

Description	Photo	Screws
3. Insert a flat screwdriver into the groove and then lift up and remove the cover.		
4. After remove COVER-REAR, then disconnect SPEAKER , FUNCTION wire. 5. Disconnect LVDS cable from panel.	   	

Description	Photo	Screws
6. After disconnecting SHIELD-LAMP of left side, disassemble lamp wire between panel and IP Board.		
7. Remove 8 marked SCREW of left picture. Disconnect IP board. ※ Reassembly procedures are in the reverse order of disassembly procedures.		
8. Remove the LCD panel.		

Description	Photo	Screws
9. Remove the IR module by tilting the left snap to the right.		
10. Remove the LED module by sliding the snap designated in the right figure backwards.	 	
11. Remove the two (2) screws and then remove the holders from the four (4) snaps designated in the right figure using the provided jig.		

Description	Photo	Screws
12. Remove the two (2) connectors. ⚠ Caution : Servicing is not supported for the PCB.		
▶Assembly 13. The assembly is in the reverse order of the disassembly. 14. Connect the disassembled snap and the LED module again.		
15. Fix the connecting wire with filament tape ⚠ Caution : If the wire is damaged when closing the cover, an operating error may occur. Therefore, make sure to close the cover after fixing it with filament tape.		

※ The assembly is in the reverse order of disassembly.

Memo

5. Exploded View & Part List

5-1. LS20TDSSUMZD - Exploded View (T220M)



5-1-1. LS20TDSSUMZD - Parts List (T220M)

Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
M0006	BN96-08149G	ASSY SHIELD P-COVER;LS20TD(ANALOG),SECC	1	S.N.A	
M0013	BN96-07447H	ASSY COVER P-REAR;LS20TD(ANALOG),PMMA AB	1	S.A	
M0014	BN94-01893R	ASSY PCB MAIN;LS20TDSSU/ZB	1	S.A	
M0027	BN96-07345B	ASSY STAND P-BASE;LS22TW,ABS HB PMMA,RD0	1	S.A	
M0090	BN96-08016A	ASSY SHIELD P-LAMP;LS20TD(MFM),SPTE,T 0.	1	S.N.A	
M0174	BN44-00177D	IP BOARD;PWI2204ST(A),T 20" MFM,1.4 ~2.8	1	S.A	
M0215	BN07-00374A	LCD-PANEL;CLAA201WA04	1	S.A	
STD	BN96-07347D	ASSY STAND P-BODY;LS22TD,PMMA ABS HB, SM	1	S.A	
T0003	BN96-07446L	ASSY COVER P-FRONT;LS20TD,BRAZIL,PMMA+AB	1	S.A	
T0279	BN63-05063A	COVER-JACK;T220M ANALOG,ABS + PC,HB,BK26	1	S.N.A	

5-2. LS20TDSSUMZD Parts List

Service Bom (SA: SERVICE AVAILABLE, SNA: SERVICE NOT AVAILABLE)

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
		LS20TDSSUMZD	T200M,WST1/S20A4-LTD,20,LCD-MO,BRAZIL			
0.1	M0001	BN90-01634H	ASSY COVER FRONT;LS20TD_MFM,TOC,ROSE BLA	1	S.N.A	
..2	M0081	6006-001096	SCREW-TAPTITE;BH,+,WP,B,M4.0,L12,ZPC(BLK	4	S.N.A	
..2	T0175	BN96-06823C	ASSY SPEAKER P;16ohm,T-project,MFM,3W,11	1	S.A	
...3		BN83-00813A	CKD-SPEAKER;Bordeaux New Rubber,pi 15 x	4	S.N.A	
...3		BN83-01026A	CKD-SPEAKER;L530 32" Fullrange Sleeve-#1	2	S.N.A	
...3		BN83-01027A	CKD-SPEAKER;L530 32" Fullrange Sleeve-#1	2	S.N.A	
...3		BN83-01322A	CKD-SPEAKER;T-MFM Speaker Unit,63mm X 35	2	S.N.A	
...3		BN83-01323A	CKD-SPEAKER;T-MFM Speaker Holder,95mm X	2	S.N.A	
...3		BN83-01324A	CKD-SPEAKER;T-MFM Speaker Wire Ass'y,4Pi	1	S.N.A	
...3		BN83-01325A	CKD-SPEAKER;T-MFM Speaker Cushion,52 X23	2	S.N.A	
...3		BN83-01326A	CKD-SPEAKER;T-MFM Speaker Label,20mmX10m	1	S.N.A	
...3		BN83-00781A	CKD-SPEAKER;Bordeax26 Screw,pi3 * 6mm	8	S.N.A	
..2	T0003	BN96-07446L	ASSY COVER P-FRONT;LS20TD,BRAZIL,PMMA+AB	1	S.A	
...3	M0081	6003-000282	SCREW-TAPTITE;BH,+,-,B,M3,L8,ZPC(BLK),SW	2	S.N.A	
...3	M0960	BN61-03932A	HOLDER-BOSS;T200,PMMA+ABS HB,WH15	1	S.N.A	
...3	CCM1	BN63-02183D	COVER-SHEET;Rhcm,PE Vinyl,T0.05,680mm,20	1	S.N.A	
...3	M0112	BN63-04426X	COVER-FRONT;LS20TD(ANALOG),PMMA+ABS,ROSE	1	S.N.A	
...3	M0145	BN96-07556D	ASSY BOARD P-FUNCTION;T220HD,CT5000-5800	1	S.A	
....4		BN94-02473F	ASSY PCB MAIN-FUNCTION PCB;LS22TDSSUMZD	1	S.N.A	
.....5	M2893	BN39-01051B	LEAD CONNECTOR;T-MFM24,UL1571#30,UL1571#	1	S.A	
.....5	T0174	BN97-02920J	ASSY SMD;LS22TDSSUMZD	1	S.N.A	
......6	D3	0406-001172	DIODE-TVS;CDS3C30GTH,48/-/50V,SMD	1	S.A	
......6	D4	0406-001172	DIODE-TVS;CDS3C30GTH,48/-/50V,SMD	1	S.A	
......6	R6	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
......6	R7	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	S.A	
......6	R1	2007-000121	R-CHIP;820ohm,5%,1/10W,TP,1608	1	S.N.A	
......6	R4	2007-000121	R-CHIP;820ohm,5%,1/10W,TP,1608	1	S.N.A	
......6	R2	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.N.A	
......6	R5	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.N.A	
......6	C3	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
......6	C4	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
......6	T0313	3404-001209	SWITCH-TACT;12VDC,50mA,250gf,4.5x4.5x1.5	1	S.A	
......6	T0313	3404-001209	SWITCH-TACT;12VDC,50mA,250gf,4.5x4.5x1.5	1	S.A	
......6	T0313	3404-001209	SWITCH-TACT;12VDC,50mA,250gf,4.5x4.5x1.5	1	S.A	
......6	T0313	3404-001209	SWITCH-TACT;12VDC,50mA,250gf,4.5x4.5x1.5	1	S.A	
......6	T0313	3404-001209	SWITCH-TACT;12VDC,50mA,250gf,4.5x4.5x1.5	1	S.A	
......6	T0313	3404-001209	SWITCH-TACT;12VDC,50mA,250gf,4.5x4.5x1.5	1	S.A	
......6	T0077	BN41-01011A	PCB MAIN;T220HD,FR-4,2L,PCB1.0,1.0T	1	S.N.A	
....4		BN94-02473K	ASSY PCB MAIN-IR PCB;LS22TDSSUMZD	1	S.N.A	
.....5	M2893	BN39-01052B	LEAD CONNECTOR;T200HD,UL1571#30,UL,5P,20	1	S.A	
.....5	M2893	BN39-01053A	LEAD CONNECTOR;T220D,UL1571#30,8P,200mm,	1	S.A	
.....5	T0174	BN97-02902J	ASSY SMD;LS22TDSSUMZD	1	S.N.A	
......6	D1	0403-000510	DIODE-ZENER;MTZJ6.2B,5.96-6.27V,500mW,DO	1	S.A	
......6	R1	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	1	S.N.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
.....6	C	2401-001507	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	1	S.A	
.....6	T0077	BN41-01013A	PCB MAIN;T220D,FR-1,1L,PCB1.0,1.6T	1	S.N.A	
.....5	D0254	0609-001204	MODULE REMOCON;HORIZONTAL,6.5mm,TR	1	S.N.A	
....4		BN94-02473N	ASSY PCB MAIN-POWER PCB;LS22TDSSUMZD	1	S.N.A	
.....5		BN81-02334A	A/S-DOUBLE SIDE TAPE;T MFM POWER,103*52,	1	S.N.A	
.....5	T0174	BN97-02902K	ASSY SMD;LS22TDSSUMZD	1	S.N.A	
.....6	R1	2007-000819	R-CHIP;390Kohm,5%,1/10W,TP,1608	1	S.N.A	
.....6	C1	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	1	S.A	
.....6	C5	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
.....6	CN330	3711-002162	HEADER-BOARD TO CABLE;BOX,2P,1R,1.25mm,S	1	S.A	
.....6	CN330	3711-005935	HEADER-BOARD TO CABLE;BOX,4P,1R,1mm,SMD-	1	S.A	
.....6	CN906	3711-006471	CONNECTOR-HEADER;BOX,5P,1R,1mm,SMD-A,AU,	1	S.N.A	
.....6	IC125	BN13-00007A	IC ASIC;ADA03,6,2.2 TO 6.5 V,-20 TO +75	1	S.N.A	
.....6	T0077	BN41-01012A	PCB MAIN;T220D,FR-4,2L,PCB1.0,1.6T	1	S.N.A	
.....5	M0102	BN96-07569B	ASSY BLU P;T220HD,A7-10040180-A0,WHITE,B	1	S.A	
...3		BN64-00843A	KNOB-GUIDE;T220HD,PMMA ABS,HB,BK23,H/GLO	1	S.N.A	
...3	T0022	BN64-00845A	KNOB CONTROL;T220HD,PMMA ABS,HB,BK23,H/G	1	S.N.A	
0.1	M0002	BN90-01635D	ASSY COVER REAR;LS20TD_MFM,ANALOG	1	S.N.A	
..2	M0013	BN96-07447H	ASSY COVER P-REAR;LS20TD(ANALOG),PMMA AB	1	S.A	
...3	M0081	6003-000282	SCREW-TAPTITE;BH,+,-,B,M3,L8,ZPC(BLK),SW	2	S.N.A	
...3		BN61-03947A	GUIDE-CONTROL;T200D / T220D / T240D / T2	2	S.N.A	
...3	CCM1	BN63-02183D	COVER-SHEET;Rhcm,PE Vinyl,T0.05,680mm,20	0.5	S.N.A	
...3	M0006	BN63-04435A	COVER-REAR;T200D,PMMA+ABS,HB,BK23,H/GLOS	1	S.N.A	
...3	T0071	BN64-00959A	INLAY-TERMINAL;T220N ANALOG,PS SHEET T0.	1	S.N.A	
...3	M0126	BN73-00096A	RUBBER-PANEL;BI19BS,RUBBER,T1.0,50~60,NT	2	S.N.A	
...3	T0151	BN64-00861A	DOOR-CONTROL;T(20W MFM),ABS HB,BK23,H/G	1	S.N.A	
..2	M0081	6003-001086	SCREW-TAPTITE;BH,+,-,B,M3,L12,ZPC(BLK),S	4	S.A	
0.1	M0135	BN91-01517B	ASSY LCD-PTZ;LS20MEW*	1	S.N.A	
..2	M0215	BN07-00374A	LCD-PANEL;CLAA201WA04	1	S.A	
0.1	M0112	BN91-02443C	ASSY SHIELD;LS20TD_MFM,TOC,ANALOG	1	S.N.A	
..2	T0279	BN63-05063A	COVER-JACK;T220M ANALOG,ABS + PC,HB,BK26	1	S.N.A	
..2	M0090	BN96-08016A	ASSY SHIELD P-LAMP;LS20TD(MFM),SPTE,T 0.	1	S.N.A	
...3		BN63-04401A	SHIELD-LAMP;T(22W MFM),SPTE,T 0.3	1	S.N.A	
...3	M0125	BN63-04772A	SHIELD-PANEL;LS20TD,SPTE,0.3	1	S.N.A	
0.1	M0017	BN91-02524G	ASSY CHASSIS;LS20TDSSU/ZB	1	S.N.A	
..2	M0081	6003-000275	SCREW-TAPTITE;BH,+,-,B,M3,L10,ZPC(BLK),S	3	S.N.A	
..2	M0081	6003-000275	SCREW-TAPTITE;BH,+,-,B,M3,L10,ZPC(BLK),S	4	S.N.A	
..2	M0081	6003-001439	SCREW-TAPTITE;BH,+,-,S,M4,L8,ZPC(WHT),SW	1	S.N.A	
..2	T0562	6046-001014	STAND OFF;#4-40,L6,NI PLT,C3601,-	4	S.N.A	
..2	M0174	BN44-00177D	IP BOARD;PWI2204ST(A),T 20" MFM,1.4 ~2.8	1	S.A	
..2	CCMM1	BN73-00143A	SILICON/RUBBER;CURIE,SILICON+ALUMINA,W13	1	S.N.A	
..2	CCMM1	BN73-00192A	SILICON/RUBBER;T-MFM,GAPPAD1500,20X20X8	1	S.N.A	
..2	M0014	BN94-01893R	ASSY PCB MAIN;LS20TDSSU/ZB	1	S.A	
...3	T0245	0202-001608	SOLDER-WIRE FLUX;LFC7-107,D0.8,99.3Sn/0.	0.025	S.N.A	
...3	CN3000	3701-001385	CONNECTOR-DSUB;15P,3R,FEMALE,STRAIGHT,AU	1	S.A	
...3	CN9001	3701-001386	CONNECTOR-DVI;24P,3R,FEMALE,AU	1	S.A	
...3	CN906	3707-001081	CONNECTOR-OPTICAL;STRAIGHT,SPDIF	1	S.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
...3	CN330	3711-006715	HEADER-BOARD TO CABLE;BOX,4P,1R,2.5mm,AN	1	S.N.A	
...3	JA330	3722-002176	JACK-PHONE;7P/4C,SN,L-BLU,STRAIGHT	1	S.A	
...3	CN3005	3722-002275	JACK-DIN;4P,SN,BLK,ANGLE	1	S.A	
...3	CN2003	3722-002680	JACK-EAR PHONE;6P,NiSn,BLK,ANGLE	1	S.A	
...3	JA333	3722-002702	JACK-PIN;3P,Ni,GRN/BLU/RED,STRAIGHT	1	S.A	
...3	JA333	3722-002781	JACK-PIN;2P(Shield),Ni,WHT/RED,straight	1	S.A	
...3	TUNER_ GASK	AA63-01388A	GASKET-EMI,SPONGE;SP-P300M,Conductive Fa	1	S.A	
...3	CIS3	BN40-00113A	TUNER;HTM-6M/13F2S,HTM-6M/13F2S,PAL M,18	1	S.A	
...3	T0510	BN97-02567B	ASSY SMD-MAIN;LS20TDSSU/ZB	1	S.N.A	
....4	SUB05	0202-001477	SOLDER-CREAM;LST309-M,-,D20~45um,96.5Sn/	2.39	S.N.A	
....4	D2006	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A	
....4	D2007	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A	
....4	D2008	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A	
....4	D2009	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A	
....4	D2022	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A	
....4	D1003	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D2003	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3003	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3004	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3006	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3007	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3008	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3009	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3010	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3011	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3012	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3013	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3014	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3015	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3016	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D3230	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D4102	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D4109	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D4110	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D4111	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D9301	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D9302	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D9303	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D9304	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D9305	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D9306	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D9307	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D9308	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A	
....4	D2010	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.N.A	
....4	D3244	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.N.A	
....4	D4112	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.N.A	
....4	D4113	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.N.A	
....4	D4114	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.N.A	
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A	
....4	D2004	0403-000002	DIODE-ZENER;VLZ5V6B,5.45/5.73V,500mW,SOD	1	S.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	D2023	0403-000002	DIODE-ZENER;VLZ5V6B,5.45/5.73V,500mW,SOD	1	S.A	
....4	D3005	0403-000002	DIODE-ZENER;VLZ5V6B,5.45/5.73V,500mW,SOD	1	S.A	
....4	D3017	0403-000002	DIODE-ZENER;VLZ5V6B,5.45/5.73V,500mW,SOD	1	S.A	
....4	D3018	0403-000002	DIODE-ZENER;VLZ5V6B,5.45/5.73V,500mW,SOD	1	S.A	
....4	D3019	0403-000002	DIODE-ZENER;VLZ5V6B,5.45/5.73V,500mW,SOD	1	S.A	
....4	D3020	0403-000002	DIODE-ZENER;VLZ5V6B,5.45/5.73V,500mW,SOD	1	S.A	
....4	D3021	0403-000002	DIODE-ZENER;VLZ5V6B,5.45/5.73V,500mW,SOD	1	S.A	
....4	D5001	0403-000002	DIODE-ZENER;VLZ5V6B,5.45/5.73V,500mW,SOD	1	S.A	
....4	D3022	0403-000258	DIODE-ZENER;BZX84C5V6,5.2-6V,225mW,SOT-2	1	S.A	
....4	D9300	0403-000579	DIODE-ZENER;BZX84C5V1,4.8-5.4V,200mW,SOT	1	S.A	
....4	D9317	0403-000579	DIODE-ZENER;BZX84C5V1,4.8-5.4V,200mW,SOT	1	S.A	
....4	D3002	0403-000771	DIODE-ZENER;VLZ6V2B,5.96-6.27V,500mW,SOD	1	S.A	
....4	D3001	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A	
....4	D3070	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A	
....4	D1002	0403-001425	DIODE-ZENER;BZX84C33,31-35V,350mW,SOT-23	1	S.A	
....4	D9329	0403-001435	DIODE-ZENER;QZX363C5V6,5.32-5.88V,200MW,	1	S.A	
....4	D9340	0403-001435	DIODE-ZENER;QZX363C5V6,5.32-5.88V,200MW,	1	S.A	
....4	D3029	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.N.A	
....4	D3030	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.N.A	
....4	Q1001	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A	
....4	Q1005	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A	
....4	Q2004	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A	
....4	Q2005	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A	
....4	Q3002	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A	
....4	Q3201	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A	
....4	Q5005	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A	
....4	Q1002	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A	
....4	Q1003	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A	
....4	Q1006	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A	
....4	Q9327	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A	
....4	Q409	0505-001170	FET-SILICON;SI9933ADY-T1,P,-20V,3.4A,0.0	1	S.A	
....4	Q409	0505-002169	FET-SILICON;Si4435BDY-T1-E3,P,-30V,-9.1A	1	S.N.A	
....4	IC105	0909-001032	IC-REAL TIME CLOCK;PCF8563,SOP,8P,4.9x3.	1	S.A	
....4	IC106	1001-001516	IC-VIDEO SWITCH;PI3HDMI201ZFE,3HDMI201 :	1	S.A	
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A	
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A	
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A	
....4	IC112	1103-001385	IC-EEPROM;AT24C256,256Kbit,32Kx8,SOP,8P,	1	S.A	
....4	IC6001	1105-001838	IC-DDR SDRAM;EM6A9160TS0A-5G,DDR SDRAM,1	1	S.A	
....4	DU410	1201-000166	IC-OP AMP;LM358,SOP,ST,8P,150MIL,DUAL,10	1	S.A	
....4	T0124	1201-002430	IC-POWER AMP;NTP-3000,QFN,56P,8x8mm,DUAL	1	S.A	
....4	T0085	1201-002487	IC-AUDIO AMP;MAX9728A,QFN,12P,3x3mm,DUAL	1	S.A	
....4	T0087	1203-001815	IC-POSI.FIXED REG.;78M09,TO-252,3P,-,PLA	1	S.A	
....4	T0087	1203-002842	IC-POSI.FIXED REG.;AP1117D-33A,TO-252,3P	1	S.A	
....4	T0087	1203-002842	IC-POSI.FIXED REG.;AP1117D-33A,TO-252,3P	1	S.A	
....4	T0087	1203-002974	IC-POSI.FIXED REG.;AP1117D-25A,TO-252,3P	1	S.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	T0170	1203-003059	IC-SWITCH VOL. REG.;MP1583,SOIC,8P,4.9x3	1	S.A	
....4	T0087	1203-003696	IC-POSI.FIXED REG.;NCP1117DT18T5G,DPAK,3	1	S.A	
....4	IC5001	1203-004363	IC-VOL. DETECTOR;RT9818C-29PV,SOT-23,3P,	1	S.A	
....4	IC2003	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A	
....4	IC1005	1203-005188	IC-DC/DC CONVERTER;AOZ1021AIL,SOP,8P,4.9	1	S.A	
....4	D2001	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D2002	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D3023	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D3024	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D3071	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D3072	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D3231	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D3232	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D3233	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D4115	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	D4117	1405-001233	VARISTOR;30Vdc,5A,1.6x0.8x0.8mm,TP	1	S.A	
....4	R1028	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R1067	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R1068	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R1071	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R6101	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R1029	2007-000067	R-CHIP;15Kohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R1002	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1004	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1063	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1064	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1301	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2013	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2066	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3001	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3002	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3003	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3004	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3005	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3006	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3007	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3008	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3010	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3066	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3259	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3260	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3261	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3264_H	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3265_H	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R4058	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R4101	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5001	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5028	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5036	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5037	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5052	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	R5057	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5065	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5999	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6012	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6014	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6066_T	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6094	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9348_F3V	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9356	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9357	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3014	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3015	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3027	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3103	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5019	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5020	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5021	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5024	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5027	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5029	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5083	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5084	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5203	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5204	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5205	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9318	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9319	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9320	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9321	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9322	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9323	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9324	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9325	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3016	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3017	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3025	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3026	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5032	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5033	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5035	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6010	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6011	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6050	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6051	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9336	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9337	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2014	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R2017	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R3013	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R3030	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R3064	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	R3065	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R4127	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5009	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5010	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5011	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5017	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5018	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5038	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5039	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5040	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5042	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5043	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5051	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5054	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5055	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5058	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5059	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5060	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5061	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5063	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5067	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5068	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5072	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5073	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R6015	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R6016	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R6020	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R6093	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R9330	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A	
....4	R1010	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	S.A	
....4	R2084	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A	
....4	R2085	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5041	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5085	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A	
....4	R2015	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2021	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2125	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2126	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3009	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3028	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3029	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5002	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R6048	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R6049	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R6052	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R6092	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R9326	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R9328	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R9352	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R9353	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3036	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	1	S.N.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	R5070	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5071	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1031	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1032	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2004	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2005	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2009	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2010	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2069	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2081	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2083	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2088	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3012	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3044	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3062	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3063	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3254	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5069	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R6041	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R6042	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1006	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1007	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1030	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1043	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1048	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1049	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2028	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2080	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2082	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2089	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2156	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2157	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3018	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3019	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3023	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3024	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3031	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3034	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3035	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3042	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3057	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3058	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3059	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3253	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R4119	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R4120	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5004	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5007	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5077	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5080	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5117	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	R5119	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R9331	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R9334	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R9335	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R4121	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R4123	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9358	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R9359	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1012	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5074	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5076	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5078	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R5081	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1015	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1016	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1008	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1011	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1040	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1041	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1042	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R1058	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R6022	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R6090	2007-000106	R-CHIP;220Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5082	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2074	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5006	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5506	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R5075	2007-000127	R-CHIP;9.1Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2019	2007-000138	R-CHIP;100ohm,5%,1/16W,TP,1005	1	S.N.A	
....4	R3074	2007-000138	R-CHIP;100ohm,5%,1/16W,TP,1005	1	S.N.A	
....4	R3283	2007-000138	R-CHIP;100ohm,5%,1/16W,TP,1005	1	S.N.A	
....4	R2077	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	S.N.A	
....4	R2078	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	S.N.A	
....4	R3284	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	S.N.A	
....4	R3285	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	S.N.A	
....4	R2075	2007-000174	R-CHIP;47ohm,5%,1/16W,TP,1005	1	S.N.A	
....4	R2076	2007-000174	R-CHIP;47ohm,5%,1/16W,TP,1005	1	S.N.A	
....4	R3011	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A	
....4	R2086	2007-000570	R-CHIP;220ohm,1%,1/10W,TP,1608	1	S.A	
....4	R2087	2007-000570	R-CHIP;220ohm,1%,1/10W,TP,1608	1	S.A	
....4	R2016	2007-000683	R-CHIP;3.3Kohm,1%,1/10W,TP,1608	1	S.A	
....4	R1070	2007-000726	R-CHIP;300ohm,1%,1/10W,TP,1608	1	S.A	
....4	R1057	2007-000839	R-CHIP;39ohm,5%,1/10W,TP,1608	1	S.A	
....4	R2001	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2002	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2003	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2006	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2007	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2008	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2011	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R2012	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.N.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	R1033	2007-000939	R-CHIP;47Kohm,1%,1/10W,TP,1608	1	S.A	
....4	R3070	2007-000950	R-CHIP;47ohm,5%,1/4W,TP,3216	1	S.A	
....4	R3071	2007-000950	R-CHIP;47ohm,5%,1/4W,TP,3216	1	S.A	
....4	R3286	2007-000950	R-CHIP;47ohm,5%,1/4W,TP,3216	1	S.A	
....4	R1069	2007-000965	R-CHIP;5.1Kohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6017	2007-001007	R-CHIP;51Kohm,1%,1/10W,TP,1608	1	S.A	
....4	R2020	2007-001093	R-CHIP;620ohm,5%,1/10W,TP,1608	1	S.A	
....4	R4103	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R4105	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R4107	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R3020	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3021	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3022	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3072	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3073	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3287	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R6027	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1003	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1022	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1023	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1025	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1026	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R1027	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	1	S.N.A	
....4	R3288	2007-007309	R-CHIP;12Kohm,1%,1/16W,TP,1005	1	S.A	
....4	R3289	2007-007309	R-CHIP;12Kohm,1%,1/16W,TP,1005	1	S.A	
....4	R6006	2011-000585	R-NETWORK;47ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	R6007	2011-000585	R-NETWORK;47ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA5008	2011-000585	R-NETWORK;47ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA5009	2011-000585	R-NETWORK;47ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA5010	2011-000585	R-NETWORK;47ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA5011	2011-000585	R-NETWORK;47ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA5012	2011-000585	R-NETWORK;47ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA6006	2011-000585	R-NETWORK;47ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA6009	2011-000585	R-NETWORK;47ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA5024	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA5026	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA5027	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA6010	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP,3.	1	S.N.A	
....4	RA5007	2011-001001	R-NETWORK;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2	1	S.A	
....4	RA5001	2011-001011	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5004	2011-001011	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5017	2011-001011	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5018	2011-001011	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5032	2011-001011	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5033	2011-001011	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5005	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5006	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5015	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5019	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5020	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5021	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	RA5023	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5028	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5029	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	RA5030	2011-001093	R-NETWORK;100ohm,5%,1/16W,L,CHIP,8P,TP,3	1	S.A	
....4	C1005	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C1047	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C1060	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C1071	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C1112	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C1120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C2004	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C2005	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C2013	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C2014	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C2015	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C2036	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C2037	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C2043	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C2082	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C3002	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C3020	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C3251	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5002	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5003	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5004	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5005	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5006	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5007	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5008	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5011	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5016	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5018	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5019	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5021	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5022	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5023	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5024	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5026	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5027	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5029	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5032	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5033	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5035	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5036	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5037	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5042	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5044	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5048	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5049	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5050	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5051	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	C5053	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5069	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5071	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5072	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5073	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5074	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5075	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5076	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5081	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5089	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5098	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5111	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5112	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5115	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5200	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C5208	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6016	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6024	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6025	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6026	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6027	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6029	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6031	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6032	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6033	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6034	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C6100	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C9309	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C9310	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C9311	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C9312	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C9313	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C9314	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C9315	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C9316	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C9338	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.N.A	
....4	C3236	2203-000233	C-CER,CHIP;0.1nF,5%,50V,C0G,1005	1	S.A	
....4	C2012	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.N.A	
....4	C2019	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.N.A	
....4	C3104	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.N.A	
....4	C3105	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.N.A	
....4	C4116	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.N.A	
....4	C4118	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.N.A	
....4	C6050	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.N.A	
....4	C6051	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.N.A	
....4	C1012	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C1019	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C1020	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C1037	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C1061	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C1058	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	C2001	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2002	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2018	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2025	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2026	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2027	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2028	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2034	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2035	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2039	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2040	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2041	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C2079	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C3253	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C5039	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C5055	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C5099	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C6015	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A	
....4	C1017	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A	
....4	C5091	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A	
....4	C5094	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A	
....4	C5100	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A	
....4	C5101	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A	
....4	C3106	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.N.A	
....4	C5014	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.N.A	
....4	C5015	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.N.A	
....4	C3007	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A	
....4	C3008	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A	
....4	C2081	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A	
....4	C2083	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A	
....4	C4104	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A	
....4	C4106	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A	
....4	C4108	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A	
....4	C1018	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C1056	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C5038	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C5040	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C5041	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	1	S.A	
....4	C2033	2203-000925	C-CER,CHIP;470nF,+80-20%,50V,Y5V,2012	1	S.A	
....4	C2080	2203-000925	C-CER,CHIP;470nF,+80-20%,50V,Y5V,2012	1	S.A	
....4	C5056	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C5057	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C5060	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C5061	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C5062	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C5063	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C5065	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C5066	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C5067	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C5113	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.N.A	
....4	C1016	2203-000979	C-CER,CHIP;47nF,10%,50V,X7R,TP,2012	1	S.N.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	C6014	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	S.N.A	
....4	C3009	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C3010	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C4122	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C4124	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C1011	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	S.A	
....4	C5000	2203-001630	C-CER,CHIP;330nF,+80-20%,16V,Y5V,1608	1	S.N.A	
....4	C1063	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.N.A	
....4	C2006	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.N.A	
....4	C2008	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.N.A	
....4	C2010	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.N.A	
....4	C2024	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.N.A	
....4	C3239	2203-002525	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1005	1	S.N.A	
....4	C3240	2203-002525	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1005	1	S.N.A	
....4	C2090	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A	
....4	C2091_22	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A	
....4	C2160	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A	
....4	C4009	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A	
....4	C5090	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A	
....4	C6006	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A	
....4	C6019	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A	
....4	C6021	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A	
....4	C1001_22	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C1022	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C1107	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C1114	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C2007	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C2009	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C2011	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C2023	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C2158	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C2159	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C5087	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C9346	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C9347	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C9354	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C9355	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.N.A	
....4	C1002	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C1064	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C2029	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C2030	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C2031	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C2032	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C2075	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C2076	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C2077	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C2078	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	1	S.N.A	
....4	C1073	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C1103	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C1123	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C1124	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	C5077	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C5078	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C5079	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C5080	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C5084	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C5085	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C5086	2203-005384	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,TP,201	1	S.N.A	
....4	C2154	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.N.A	
....4	C2155	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.N.A	
....4	C2044	2203-005809	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	1	S.A	
....4	C5047	2203-005809	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	1	S.A	
....4	C5207	2203-005809	C-CER,CHIP;1000nF,10%,16V,X7R,-,2012	1	S.A	
....4	C1052	2203-005834	C-CER,CHIP;22000nF,+80-20%,10V,Y5V,3216	1	S.A	
....4	C1053	2203-005834	C-CER,CHIP;22000nF,+80-20%,10V,Y5V,3216	1	S.A	
....4	C1065	2203-005834	C-CER,CHIP;22000nF,+80-20%,10V,Y5V,3216	1	S.A	
....4	C1066	2203-005834	C-CER,CHIP;22000nF,+80-20%,10V,Y5V,3216	1	S.A	
....4	C2020	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	S.N.A	
....4	C2021	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	S.N.A	
....4	C1003	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1007	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1010	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1014	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1035	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1036	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1038	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1039	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1046	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1048	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1050	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1051	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1059	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1068	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C2092	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	S.A	
....4	C1075	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C1104	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C1109	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C1110	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C2016	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C2017	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C2042	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C2161	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C3001	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C3019	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C3250	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C4010	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C5013	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C5088	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C9337	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	1	S.A	
....4	C1055	2203-006708	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,1608	1	S.A	
....4	C1057	2203-006708	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,1608	1	S.A	
....4	C1121	2203-006708	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,1608	1	S.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	C1122	2203-006708	C-CER,CHIP;4700nF,+80-20%,10V,Y5V,1608	1	S.A	
....4	C1004	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C1006	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C1008	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C1009	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C1013	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C1015	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C1049	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C5201	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C5202	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C5203	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C5204	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C5205	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C6003	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C6028	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C6049	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C6075	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012 (	1	S.N.A	
....4	C6001	2402-001216	C-AL,SMD;470uF,20%,16V,WT,TP,10.3x10.3x1	1	S.A	
....4	C1021	2402-001238	C-AL,SMD;1uF,20%,50V,HR,TP,4.3x4.3x5.2mm	1	S.N.A	
....4	C2003	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10mm	1	S.A	
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A	
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A	
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A	
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A	
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A	
....4	T0052	2703-000417	INDUCTOR-SMD;220uH,5%,3225	1	S.A	
....4	T0052	2703-001334	INDUCTOR-SMD;1.5uH,10%,2012	1	S.A	
....4	T0052	2703-001426	INDUCTOR-SMD;680uH,20%,7070	1	S.A	
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A	
....4	T0052	2703-002722	INDUCTOR-SMD;22uH,20%,12x12mm	1	S.A	
....4	T0052	2703-002916	INDUCTOR-SMD;10uH,20%,8080	1	S.A	
....4	T0052	2703-003362	INDUCTOR-SMD;4.7uH,20%,7070	1	S.A	
....4	L2001	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A	
....4	L2002	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A	
....4	X202	2801-003667	CRYSTAL-SMD;14.31818MHz,30ppm,28-AAN,16p	1	S.A	
....4	F103	2901-001114	FILTER-EMI SMD;25VDC,2.0ADC,-,100nF,3.2x	1	S.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A	
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A	
....4	T0568	3301-001793	BEAD-SMD;18ohm,1608,-,TP,11.8ohm/37.6MHz	1	S.A	
....4	T0568	3301-001793	BEAD-SMD;18ohm,1608,-,TP,11.8ohm/37.6MHz	1	S.A	
....4	T0568	3301-001793	BEAD-SMD;18ohm,1608,-,TP,11.8ohm/37.6MHz	1	S.A	
....4	CN3001	3701-001367	CONNECTOR-HDMI;19P,2R,FEMALE,SMD,AU	1	S.A	
....4	M0106	3708-001150	CONNECTOR-FPC/FFC/PIC;30P,1mm,SMD-A,SN,Y	1	S.A	
....4	CN330	3711-005499	HEADER-BOARD TO CABLE;BOX,8P,1R,1.25mm,S	1	S.N.A	
....4	CN330	3711-005503	HEADER-BOARD TO CABLE;BOX,9P,1R,2mm,SMD-	1	S.N.A	
....4	T0077	BN41-01068B	PCB MAIN;T-MFM,FR-4,230*180,22 sound_imp	1	S.N.A	
....4	MAIN_ MICOM	BN97-02752A	ASSY MICOM-MAIN;LS20TDSSU/ZB	1	S.N.A	
.....5	IC115	1107-001709	IC-FLASH MEMORY;MX25L1605A,16Mbit,2Mx8,S	1	S.N.A	
....4	T0087	1203-003060	IC-POSI.FIXED REG.;AP1084,TO-263,3P,9.97	1	S.A	
....4	IC109	1205-003308	IC-LCD CONTROLLER;SEMP690-LF,LQFP,256P,2	1	S.A	
....4	R2162	2007-000131	R-CHIP;91Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R2163	2007-000131	R-CHIP;91Kohm,5%,1/10W,TP,1608	1	S.A	
....4	R3251	2007-000239	R-CHIP;1.5Kohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R1021	2007-000503	R-CHIP;2.2ohm,5%,1/10W,TP,1608	1	S.A	
....4	R5034	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.N.A	
....4	R6013	2007-007651	R-CHIP;9.1Kohm,1%,1/10W,TP,1608	1	S.A	
....4	C9345	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,TP,1608	1	S.N.A	
....4	X202	2801-000258	CRYSTAL-SMD;0.032768MHz,20ppm,SMD,12.5pF	1	S.N.A	
...3	T0066	BP62-00047A	HEAT SINK-ES;DLP,A6063S,T2.5,13,13,TAPE	1	S.N.A	
...3	JA333	3722-002267	JACK-PIN;3P,AU,RED/WHT/YEL,ANGLE	1	S.A	
...3	T0066	BP62-00017A	HEAT SINK-ES;SP-50L2HX,A6063S,T2.0,26.2,	1	S.N.A	
..2	M0214	BN96-07252B	ASSY CABLE P-FLAT;LIME,Flat cable,100mm,	1	S.A	
..2	M0006	BN96-08149G	ASSY SHIELD P-COVER;LS20TD(ANALOG),SECC	1	S.N.A	
...3	T0073	BH63-00008A	GASKET-EMI;IB10LO,CONDUCTIVE FABRIC,3MM,	1	S.N.A	
...3	M0131	BH63-00104A	GASKET;POSEIDON,CONDUCTIVE FABRIC,2MM,10	4	S.N.A	
...3		BN61-02429F	STUD-PEM;PNB,M2.8,D7,L28,ZPC(SIL),SUM24L	1	S.N.A	
...3	M0114	BN61-02500A	HOLDER-WIRE;NYLON6.6,NATURAL	1	S.N.A	
...3		BN61-03869A	SPRING ETC-STAND;LS22AQ,SUS 304,T0.3,SIM	1	S.N.A	
...3		BN61-03936A	BRACKET-STAND FRAME;LS20TD,SECC,T 1.6	1	S.N.A	
...3	M0107	BN63-04406H	SHIELD-COVER;T200M ANALOG,SECC,T 0.8	1	S.N.A	
...3		BN61-02429D	STUD-PEM;PNB,M2.8,D7,L20,ZPC(SIL),SUM24L	2	S.N.A	
..2		BN73-00024C	SILICON/RUBBER-BERGQUIST;VENUS 32,40",SI	1	S.N.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
0.1	M0019	BN92-03362A	ASSY LABEL;LS22TWHSUV/EN	1	S.N.A	
0.1	M0113	BN92-03420B	ASSY P/MATERIAL;LS20TDNSUV/ZA	1	S.N.A	
..2	T0524	6902-000241	BAG PE;HDPE/NITRON,T0.5/T0.012,W600,L600	1	S.N.A	
0.1		BN92-04035B	ASSY ACCESSORY-STZ;LS22TDSSUMZD	1	S.N.A	
..2	M0114	BN39-00244G	CBF SIGNAL;D-sub cable,15P/15P,20276N,15	1	S.A	
..2	M0027	BN96-07345B	ASSY STAND P-BASE;LS22TW,ABS HB PMMA,RD0	1	S.A	
...3	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	4	S.N.A	
...3	CIS4	BN61-01717A	HOLDER-STAND;BIZET,NI PLT,CH,+,M4,L11(5)	1	S.N.A	
...3		BN61-03907A	BRACKET-STAND BOTTOM;T22W,SECC,T 0.8	1	S.N.A	
...3	T0004	BN63-04390A	COVER-STAND BASE;T220,PMMA+ABS,HB,RD02,H	1	S.N.A	
...3	CCM1	BN63-02183K	COVER-SHEET;Rhcm,PE Vinyl,T 0.05,250MM,2	0.3	S.N.A	
...3	T0132	BN73-00077A	RUBBER FOOT;MATISSE,BUMPON,Φ13.5,T2.0,6	4	S.N.A	
..2	STD	BN96-07347D	ASSY STAND P-BODY;LS22TD,PMMA ABS HB, SM	1	S.A	
...3	M0081	6003-000275	SCREW-TAPTITE;BH,+,-,B,M3,L10,ZPC(BLK),S	5	S.N.A	
...3		BN63-04404A	COVER-STAND FRONT;T200D / T22OD,PMMA+ABS	1	S.N.A	
...3		BN63-04407A	COVER-STAND REAR;T200D , T220D,PMMA+ABS,	1	S.N.A	
...3	T0054	BN96-07341B	ASSY HINGE P;LS22TW,SM50 T2.0	1	S.N.A	
...3	CCM1	BN63-02183K	COVER-SHEET;Rhcm,PE Vinyl,T 0.05,250MM,2	0.25	S.N.A	
..2		BN96-09196A	ASSY ACCESSORY-STZ;LS22TDSSUMZD	1	S.A	
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,W250,L400,TRP,28,2,-,9	1	S.N.A	
...3	T0128	BN39-00061C	CBF SIGNAL-STEREO;Mckinley,1,male,1.5m,B	1	S.A	
...3		BN59-00804A	S/W DRIVER-01,IB;T200M,T220M,S.America,S	1	S.N.A	
...3	M9889	BN63-01798B	CLOTH-CLEAN;cloth,180,200,sea blue,ToC	1	S.N.A	
...3		BN68-00844A	MANUAL FLYER-01, LEAFLET;LCD/CDT Leaflet	1	S.N.A	
...3	T0268	3903-000020	CBF-POWER CORD;DT,BR,BP3/YES,I(IEC320 C1	1	S.A	
...3	M0114	BN61-03555A	HOLDER-WIRE;MCKINLEY,ABS HB,BK26	1	S.N.A	
...3		BN98-01071A	ASSY K/D-REMOCON;BN59-00678A,CORAL,BRAZI	1	S.N.A	
....4	M0014	BN94-01943A	ASSY PCB MAIN;BN98-01071A	1	S.N.A	
.....5		AA83-00266A	CKD-HOLDER WIRE;URETHAN CLARITY	1	S.N.A	
.....5		AA83-00321A	CKD-RUBBER-KEY PAD;BN59-00678A	1	S.N.A	
.....5		AA83-00322A	CKD-B/SPRING COMMON;BN59-00678A	1	S.N.A	
.....5		AA83-00325A	CKD-BAG-PE;BN59-00678A	1	S.N.A	
.....5	T0174	BN97-02333A	ASSY SMD;BN98-01071A	1	S.N.A	
......6		AA83-00256A	CKD-IR-LED;Φ5.0	1	S.N.A	
......6		AA83-00258A	CKD-IC;GC46C501G0	1	S.N.A	
......6		AA83-00259A	CKD-CHIP-RESISTOR;RC2012J,0R0CS	1	S.N.A	
......6		AA83-00260A	CKD-CHIP-CAPACITOR;CL 21C 104ZBC NNNC	1	S.N.A	
......6		AA83-00261A	CKD-RESONATOR;ZTT3.64MG	1	S.N.A	
......6		AA83-00262A	CKD-ELE-CAPACITOR;SHL 16V 47uF 5.0Φ	1	S.N.A	
......6		AA83-00310A	CKD-PCB;BN59-00678A	1	S.N.A	
......6		AA83-00323A	CKD-B/SPRING - (+);BN59-00678A	1	S.N.A	
......6		AA83-00324A	CKD-B/SPRING - (-);BN59-00678A	1	S.N.A	
.....5	T0501	AA63-01682A	COVER-TOP;TM95,ABS +PMMA,HB,BLACK	1	S.A	
.....5	T0531	AA63-01690A	COVER-BOTTOM;TM95,ABS +PMMA,HB,BLACK	1	S.A	
.....5	M0006	AA63-01687A	COVER-REAR SUB;TM95,ABS +PMMA,HB,BLACK	1	S.N.A	
.....5	T0603	AA64-04519A	WINDOW-RMC;TM95,PC,HB,VIOLET	1	S.N.A	
...3		BN68-01812A	MANUAL FLYER-02,QSG;T200M,T220M,SyncMast	1	S.N.A	

Level	Location No.	Code No.	Description & Specification	Q'ty	SA/SNA	Remark
0.1	M0003	BN92-04235A	ASSY BOX;LS20TDSSUMZD	1	S.N.A	
..2		BN69-03094B	BOX-SET;T200M,CB,A-01,SW-50,W547,D491,H1	1.02	S.N.A	

6. Wiring Diagram

6-1. Wiring Diagram - Main Board



6-2. Wiring Diagram - IP Board



6-3. Connector Functions

Connector	Functions
CN5002	Transmits LVDS signals from the Main board to the panel * When a problem occurs: The Blank Screen and No Power errors may occur.
CN3000	VGA signal input terminal * When a problem occurs: The No RGB Output error may occur.
CN9001	DVI signal input terminal * When a problem occurs: The No DVI Output error may occur.
CN3001	HDMI signal input terminal * When a problem occurs: The No HDMI Output error may occur.
CN1001	Supplies 5V and 13V from the Power board to the Main board. Receives and transmits the PWM output to the Inverter. * When a problem occurs: The Blank Screen and No Power errors may occur.
CN4002	Component input terminal. * When a problem occurs: The No Component Video Input error may occur.
JA3003	PC Audio input terminal. * When a problem occurs: The No PC Sound Output error may occur.
OP4001	Digital Audio output terminal. * When a problem occurs: The No Digital Audio Operating error may occur.
CN4001	Component Audio input terminal. * When a problem occurs: The No Component Sound Output error may occur.
CN2003	Headphone output terminal.

6-4. Cables

Use	LVDS 30P FFC cable	
Code	20” : BN96-07252B	22” : BN96-07252D
Photo		

Memo

4. Troubleshooting

4-1. First Checklist for Troubleshooting

1. Check the various cable connections first.
   - Check to see if there is a burnt or damaged cable.
   - Check to see if there is a disconnected cable connection or a connection is too loose.
   - Check to see if the cables are connected according to the connection diagram.
2. Check the power input to the Main Board.
3. Check the following circuits.
   • No raster appears: Function PBA, Main PBA, I/P PBA
   • 55V develop but no screen: Main PBA
   • 5V does not develop: I/P PBA
4. Check the voltage in and out between the IP↔ Main Board, between the IP↔ Panel, and between the Main LVDS Boards.

4-2. No Power

Symptom	– Though the power swtich on, the LED power off and the screen is blank.
Major checkpoints	– Check Power cable. – Check whether the Lamp connector is connected correctly to the IP. – Check whether the power cable is connected correctly to the MAIN. – Check whether the Function cable is connected correctly to the MAIN.
Diagnostics	 Main Board Front Does Power indicator LED Off ? → No → Check a connection a power cable. Yes ↓ Does proper DC 14.5V appear at C1002. → No → Change a Assy PCB Power. Yes ↓ Does proper DC5V appear at C1004? → No → Change a Assy PCB Power. Yes ↓ Does proper DC3.3V, 1.2v appear at 1112, C1052? → No → Check IC1013, IC1005. Change a main PBA. Yes ↓ A power is supplied to set? → No → Check a other function.(No picture part) Replace a lcd panel.
Caution	Make sure to disconnect the power before working on the IP board.

4-2-1. Circuit diagrams when the power does not turn on





4-3. No Video (Analog PC)

Symptom	– Though the LED power turns on, the screen is blank when connecting the VGA cable.
Major checkpoints	– Even though the LED power turns on, the screen is blank when connecting the VGA cable. – Check the D-sub cable connections. – Check whether the LVDS cable is connected correctly to the panel. – Check whether the lamp connector of the panel is connected correctly to the IP board.
Diagnostics	 Main Board Front Power Indicator is off. Lamp on, no video. Yes Check a PC source and check the connection of DSUB cable? — No → Input a analog PC signal and connected cable(DPMS). Yes ① Does the sigmal appear at R3020, R3021,R3022? — No → PC cable. Change a PC cable. Change a main PCB ass'y. Yes Does the digital data appear at the output of RA5008~RA5012? — No → Check IC5002. Change a main PBA. Yes Check a LVDS cable? Replace a lcd panel? — No → Please, Call to Samsung Co. LTD.
Caution	Make sure to disconnect the power before working on the IP board.

4-3-1. Circuit diagrams and waveforms (Analog) when no screen is displayed on the monitor

DSUB_INPUT







4-3-2. Waveforms when no screen is displayed (Analog PC)

① R,G,B Output Signal of IC5002



4-4. No Video (Digital-HDMI)

Symptom	– The LED power turns on but the screen is blank when the DVI cable or HDMI cable is connected.
Major checkpoints	– Even though the LED power turns on, the screen is blank when connecting the DVI cable or HDMI cable. – Check the DVI cable or HDMI cable connections. – Check whether the LVDS cable is connected correctly to the panel. – Check whether the lamp connector of the panel is connected correctly to the IP board.
Diagnostics	 Main Board Front Power Indicator is off. Lamp on, no video. Yes Check the connection of HDMI cable? — No → Input a HDMI cable. Yes ② Does the digital data appear at D3006~D3013 (HDMI1)? — No → Check HDMI cable. Change the cable. Yes Does the digital data appear at output of IC5002? — No → Check the IC5002. Change a main PBA. Yes Check a LVDS cable? Replace lcd panel? — No → Please, Call to Samsung Co. LTD.
Caution	Make sure to disconnect the power before working on the IP board.

4-4-1. Circuit diagrams and waveforms (Digital-HDMI) when no screen is displayed on the monitor



4-4-2. Waveforms when a blank screen is displayed (Digital-HDMI)

② Digital Output Data of IC3250



③ Signal of HDMI(Data)



4-5. No Picture (Tuner_CVBS)

Symptom	– The LED power turns on but the screen is blank when the RF cable is connected.
Major checkpoints	– Even though the LED power turns on, the screen is blank when connecting the RF cable. – Check the RF cable connections. – Check whether the LVDS cable is connected correctly to the panel. – Check whether the lamp connector of the panel is connected correctly to the IP board.
Diagnostics	 Main Board Front Power Indicator is off. Lamp on, no picure. → No → Connect the RF cable and check RF signal. Yes ④ Does the signal appear at L6001? → No → Check the Tuner Vcc 5V. Change a main PBA. Yes ④ Does the signal appear at #9 of TU6001? → No → Change a main PCB ass'y. Yes ③ Does the digital data appear at output of RA5008 ~RA5012? → No → Check a IC5002. Change a main PCB ass'y. Yes Check a LVDS cable? Replacea lcd panel? → No → Please, Call to Samsung Co. LTD.
Caution	Make sure to disconnect the power before working on the IP board.

4-5-1. Circuit diagrams and waveforms (Tuner_CVBS) when no screen is displayed on the monitor



4-5-2. Waveforms when a blank screen is displayed (Tuner_CVBS)

③ CVBS Output Signal



④ Tuner_CVBS Output Signal



4-6. No Picture (AV)

Symptom	– The LED power turns on but the screen is blank when the Antenna Cable is connected.
Major checkpoints	– Even though the LED power turns on, the screen is blank when connecting the Antenna Cable. – Check the Antenna Cable connections. – Check whether the LVDS cable is connected correctly to the panel. – Check whether the lamp connector of the panel is connected correctly to the IP board.
Diagnostics	 Main Board Front Power Indicator is off. Lamp on, No signal image. → No → check antenna cable ↓ Yes ④ Does the AV signal appear at #52pin of IC5002? → No → check antenna cable Change a main PBA ↓ Yes Check a LVDS cable? Replace lcd panel? → No → Please, Call to Samsung Co. LTD.
Caution	Make sure to disconnect the power before working on the IP board.

4-6-1. Circuit diagrams and waveforms (AV) when no screen is displayed on the monitor

SIDE-AV
CN3002

3722-002267



4-6-2. Waveforms when a blank screen is displayed (AV)

④ CVBS Output Signal



4-7. No Picture (S-VIDEO)

Symptom	– The LED power turns on but the screen is blank when the Antenna Cable is connected.
Major checkpoints	– Even though the LED power turns on, the screen is blank when connecting the Antenna Cable. – Check the Antenna Cable connections. – Check whether the LVDS cable is connected correctly to the panel. – Check whether the lamp connector of the panel is connected correctly to the IP board.
Diagnostics	 Main Board Front Power Indicator is off. Lamp on, No signal image. → No → check antenna cable ↓ Yes ④ Does the S–VIDEO signal appear at #50, 51 pin of IC5002? → No → check antenna cable Change a main PBA ↓ Yes Check a LVDS cable? Replace lcd panel? → No → Please, Call to Samsung Co. LTD.
Caution	Make sure to disconnect the power before working on the IP board.

4-7-1. Circuit diagrams and waveforms (S-VIDEO) when no screen is displayed on the monitor



4-7-2. Waveforms when a blank screen is displayed (S-VIDEO)

④ CVBS Output Signal



4-8. No Picture (Component)

Symptom	– The LED power turns on but the screen is blank when the Antenna Cable is connected.
Major checkpoints	– Even though the LED power turns on, the screen is blank when connecting the Antenna Cable. – Check the Ant enna Cable connections. – Check whether the LVDS cable is connected correctly to the panel. – Check whether the lamp connector of the panel is connected correctly to the IP board.
Diagnostics	 Main Board Front Power Indicator is off. Lamp on, No signal image. → No → check antenna cable ↓ Yes ④ Does the Component signal appear at #44, 46, 47 pin of IC5002? → No → check antenna cable Change a main PBA ↓ Yes Check a LVDS cable? Replace lcd panel? → No → Please, Call to Samsung Co. LTD.
Caution	Make sure to disconnect the power before working on the IP board.

4-8-1. Circuit diagrams and waveforms (Component) when no screen is displayed on the monitor



4-8-2. Waveforms when a blank screen is displayed (Component)

④ CVBS Output Signal



4-9. No Sound

Symptom	– The LED power turns on but the screen is blank when the DVI cable is connected.
Major checkpoints	– Even though the LED power turns on, the screen is blank when connecting the DVI cable. – Check the DVI cable connections. – Check whether the LVDS cable is connected correctly to the panel. – Check whether the lamp connector of the panel is connected correctly to the IP board.
Diagnostics	 Main Board Front Picture is display, no sound. → No → Connect a sound cable. control a volume. ↓ Yes ⑥ Does the signal appear at Pin #71,72,73,74,76,77,78,79 of IC5002? → No → Check a connection harness. ↓ Yes Check the 3.3V of #25 IC2005. → No → check IC2003. Change a main PBA. ↓ Yes ⑦ check output signal of #36,37,31,30,54,53,48,47 of IC2005 → No → check IC2005. ↓ Yes Replace the speaker ass'y?
Caution	Make sure to disconnect the power before working on the IP board.

4-9-1. Circuit diagrams and waveforms (No Sound) when no screen is displayed on the monitor







4-9-1. Waveforms when a blank screen is displayed (No Sound)

⑥ The Signal are Inputed to IC5002



⑦ DC 3.3V



4-10. Faults and Corrective Actions

Fault Photo	Symptoms and Corrective Actions	Remarks
	Symptoms: DVI signals are not recognized. Causes: This fault occurs when the PC does not recognize the mode information because the DVI DDC has not been input to the monitor. Corrective Actions: Input the DVI DDC to the monitor.	* Refer to the Training Manual for information on inputting the DVI DDC.
	Symptoms: When the monitor is turned on, only a full white pattern is displayed continually regardless of the signals. Causes: This fault occurs when only the lamp power is supplied and no video signals are input to the panel due to a fault or incorrect connections of the LVDS cable. Corrective Actions: Replace or reconnect the LVDS cable correctly so that video signals can be supplied to the panel.	* A full white pattern is a feature of the TN panel and is displayed when no video signals are supplied.
	Symptoms: When connecting the DVD, noise occurs on the screen. Causes: The HDCP key is not inserted. Corrective Actions: Enter the HDCP key. (See page 4-17.)	

4-11. Adjustment

4-11-1. Service Instruction

1. Usually, a color TV-VCR needs only slight touch-up adjustment upon installation.
   Check the basic characteristics such as height, horizontal and vertical sync.
2. Use the specified test equipment or its equivalent.
3. Correct impedance matching is essential.
4. Avoid overload. Excessive signal from a sweep generator might overload the front-end of the TV. When inserting signal markers, do not allow the marker generator to distort test result.
5. Connect the TV only to an AC power source with voltage and frequency as specified on the backcover nameplate.
6. Do not attempt to connect or disconnect any wire while the TV is turned on. Make sure that the power cord is disconnected before replacing any parts.
7. To protect aganist shock hazard, use an isolation transform.

4-12. How to Access Service Mode

4-12-1. Entering Factory Mode

2. To enter “Service Mode” Press the remote -control keys in this sequence :
   - If you do not have Factory remote - control



- If you have Factory remote - control

- The buttons are active in the service mode.

1. Remote - Control Key : Power, Arrow Up, Arrow Down, Arrow Left
   Arrow Right, Menu, Enter, Number Key(0~9)
2. Function - Control Key : Power, CH +, CH -, VOL +, VOL -, Menu, TV/VIDEO(Enter)

4-13. Service Adjustment

4-13-1. White Balance - Calibration

If picture color is wrong, do calibration first.

Equipment : CA210, Patten : chess pattern
Execute calibration in Factory Mode
Source PC : 1024*768/60Hz



(Gray patten)

4-13-2. White Balance - Adjustment

If picture color is wrong, check White Balance condition.

Equipment : CA210, Patten : Toshiba
Adjust W/B in Factory Mode

Sub brightness and R/G/B Offset controls low light region
Sub contrast and R/G/B Gain controls high light region
Source AV : PAL composite, Component : 1280*720/60Hz
HDMI[DVI] : 1280*720/60Hz



Toshiba Patten

[Test Pattern : MSPG-945 Series Pattern #16]

*Color temperature
1500K +/-500, -6 ~-20 MPCD

*Color coordinate
H/L : 272/278 +/- 2 35.0 Ft +/- 2.0Ft
L/L : 272/278 +/- 3 1.5 Ft +/- 0.2Ft

4-13-3. Conditions for Measurement

1. On the basis of toshiba ABL pattern : High Light level (57 IRE)
- INPUT SIGNAL GENERATOR : MSPG-925LTH

* Mode NO 2 : 744X484@60 Hz
NO 6 : 1280X720@60 Hz
NO 21 : 1024X768@60 Hz

* Pattern NO 36 : 16 Color Pattern
NO 16 : Toshiba ABL Pattern

2. Optical measuring device : CA210 (FL)

Please use the MSPG-925 LTH generator for model LE26M51B/LE32M51B/LE40M51B/LE46M51B.

4-13-4. Method of Adjustment

1. Adjust the white balance of AV, Component Modes.
   (AV→Component)
   a) Set the input to the mode in which the adjustment will be made.
      (RF→DTV→PC→DVI).

* Input signal - VIDEO Mode : Model #2 (744*484 Mode), Pattern #16
  - DTV,DVI Mode : Model #6 (1280*720 Mode), Pattern #16
  - HDMI Mode: Model #6(1280*720 Mode), Pattern #16

   b) Enter factory color control, confirm the data.

   c) Adjust the low light. (Refer to table 1, 2 in adjustment position by mode)
      - Adjust sub - Brightness to set the 'Y' value.
      - Adjust red offset ('x') and blue offset ('y') to the color coordinates.



Picture 4-2 Toshiba ABL Pattern

* Do not adjust green offset data.

   d) Adjust the high light. (Refer to table 1, 2 in adjustment position by mode)
      - Adjust red gain ('x') and blue gain ('y') to the color coordinates.

* Do not adjust the green gain and sub-contrast (Y) data.

   d) Adjust the high light. (Refer to table 1, 2 in adjustment position by mode)
      - Adjust red gain ('x') and blue gain ('y') to the color coordinates.

* Do not adjust the green gain and sub-contrast (Y) data.



Picture 4-3 Toshiba ABL Pattern

4-14. Software Upgrade

4-14-1. How to Update Flash ROM

1. Install the Flash Downloader
   Connector Set(D-SUB) and D-SUB cable to execute Program Update.



2. Flash Downloader program update
   - Turn on the TV Set
   - Click “Connect” icon on the MSTAR tool.
   - Click “Read”, and Choose a new S/W.
   - Click “Auto”, and “Run”



7. Schematic Diagram

7-1. Circuit Descriptions



7-2. Block description



T-MFM consists of three main blocks

1. Main board : Video signal processing
2. IP board : Power supply & Inverter
3. T-con board : LCD Panel control

7-3. Schematic Diagrams

This Document can not be used without Samsungs authorization.





OE	SEL1	SEL2	HPDA	HPDB
0	1	X	HPD_SINK	L
0	0	1	L	HPD_SINK
0	0	0	L	L

OC_S2	OC_S1	OC_S0	V_SWING	DE_EMPHASIS
0	0	0	500	0























BN40-00113A



FUNCTION